



FIG. 3

Item Part No.	Description	Item Part No.	Description
1	300020 Filter Choke (L-3)	33	84265 7 Prong Large Socket (S-3)
2	500002 Locating Pin	34	82428 2200 Ohms ± 10% ½ W. (R-12)
3	86121 .1 Mfd. ± 10% 600 V. (C-17)	35	86118 .25 Mfd. ± 10% 100 V. (C-4)
4	86070 .01 Mfd. ± 10% 1000 V. (C-19)	36	86118 .25 Mfd. ± 10% 100 V. (C-5)
5	82674 10,000 ohms ± 5% ½ Watt (R-22)	37	500075 Treble Choke Auxem. (L-1)
6	300007 4 Prong Plug (P-1)	38	500075 Bass Control Switch (SW-2)
7	302038 4 Lug Terminal Strip	39	82666 100,000 Ohms ± 5% ½ W. (R-4)
8	86121 .1 Mfd. ± 10% 600 V. (C-18)	40	500072 Treble Control Switch (SW-1)
9	302037 4 Lug Terminal Strip	41	300039 4 Lug Terminal Strip
10	82674 10,000 ohms ± 5% ½ Watt (R-21)	42	82430 1500 Ohms ± 10% ½ W. (R-13)
11	82675 82000 ohms ± 5% ½ Watt (R-20)	43	84263 Octal Socket (6J7)
12	84261 Octal Socket (6L6G)	44	86119 .1 Mfd. ± 10% 100 V. (C-14)
13	81084 125 ohm ± 10% W.W. 5 W. (R-23)	45	87564 20 Mfd. 25 V. Lytic (C-8)
14	82675 82,000 ohms ± 5% ½ Watt (R-24)	46	86119 .1 Mfd. ± 10% 100 V. (C-6)
15	302036 Spacer	47	82240 470 Ohms ± 10% ½ Watt (R-5)
16	300040 Input Transformer (T-2)	48	300060 4 Lug Terminal Strip
17	82465 2.7 Megohms ± 10% ½ W. (R-8)	49	82424 1000 Ohm ± 10% ½ Watt (R-9)
18	86120 .02 Mfd. ± 20% 400 V. (C-7)	50	82453 .27 Megohm ± 10% ½ W. (R-26)
19	84200 7 Prong Socket Small (Spoke.) (S-5)	51	82426 1500 Ohms ± 10% ½ W. (R-16)
20	82120 .02 Mfd. ± 20% 400 V. (C-20)	52	84262 Octal Socket (6SN7)
21	86119 .1 Mfd. ± 10% 100 V. (C-3)	53	82412 100 Ohms ± 10% ½ W. (R-25)
22	86119 .1 Mfd. ± 10% 100 V. (C-15)	54	50069 3 Lug Terminal Strip
23	82465 2.7 Megohms ± 10% ½ W. (R-1)	55	84264 Octal Socket (5U4G)
24	85079 250 Mmfd. ± 10% 400 V. Mica (C-1)	56	300008 6 Prong Socket (S-1)
25	82464 2.2 Megohms ± 10% ½ W. (R-3)	57	300061 Fuse Receptacle
26	82458 .68 Megohm ± 10% ½ W. (R-2)	58	82640 27,000 Ohms ± 5% ½ W. (R-7)
27	84203 5 Prong Socket (P.U.) (S-2)	59	82457 .56 Megohm ± 10% ½ W. (R-6)
28	86116 .003 Mfd. ± 10% 100 V. (C-2)	60	86117 .1 Mfd. ± 20% 400 V. (C-9)
29	86115 .5 Mfd. ± 10% 100 V. (C-16)	61	82434 6800 Ohms ± 10% ½ W. (R-17)
30	82418 330 Ohms ± 10% ½ Watt (R-10)	62	82815 10,000 Ohms ± 10% 2 W. (R-18)
31	82457 .56 Megohm ± 10% ½ W. (R-15)	63	82746 1000 Ohms ± 10% 1 Watt (R-19)
32	82422 680 Ohms ± 10% ½ Watt (R-11)		

ITEM PART NO.	DESCRIPTION	ITEM PART NO.	DESCRIPTION
1	Choke & Governor Arm.	15	6FD Electrode
2	5 Prong Socket (P.U.)	16	Cond.—100 Volt
3	7 Prong Large Socket	17	Leads Mg. Plate
4	4 Prong Socket (SPER)	18	See Table
5	100000 Triac Control Transformer	19	Type 4T Tube
6	80000 Triac Control Transformer	20	Grid City
7	7 Prong Small Socket (SPER)	21	Grid Cap Shield
8	500000 Output Transformer	22	6SN7GT Type 6SN7GT Tube
9	Spacer	23	6 Prong Receptacle
10	See Table	24	600000 Shoulder Screw
11	Type 6L6G Tube	25	500000 Triac Transformer
12	600000 Triac Transformer	26	500000 Type 504G Tube
13	600000 Grid	27	500000 Fuse Receptacle
14	600000 20 MFD.—100 V. & 20 MFD.—25 V. Electrolytic Cap.	28	500000 2 Amp. Fuse (1A6)